

# **MICROH**

PROFESSIONAL PRODUCTS

[www.microhpro.com](http://www.microhpro.com)



## **USER MANUAL**

**LEDP64KDII/LEDP64SDII**

**black**

**silver**

# LEDP64KDII Manual

This device is lighting effect which can create decorative effects, it is designed for club, stage and other entertainment hall.

## Specification:

1. Weight: 2.5kg
2. Size: 28X26.5X37 cm
3. Power input: **AC 120V 60Hz**
4. Wattage: 30W
5. LEDS: ultra bright 10mm, 181PCS RGB (36 RED, 85 GREEN, 60 BLUE) 40 degree
6. 3PIN female XLR socket and 3PIN male XLR socket
7. Built-in microphone
8. Led display

## Operation:



1, By using MODE button to choose the required working mode, then using UP and DOWN to adjust the relative reference date :

A . Color Choose : under this mode ,LED display show “C.L.X”, “X”=0-7, press UP or DOWN button to adjust “X”.

0---BLACK 1---RED 2---green 3---blue 4---purple 5---yellow 6---cyan 7---white

B . Color change: under this mode, the display show “J. X X”, “X X”=01-99 means the speed of color change, press UP or DOWN button to adjust the speed of color change.

C . Color fade: under this mode, led display show “F.X.X”, “X X”=( 01~99 )means the speed of color fade, press UP or DOWN button to adjust the speed of color fade.

D . Auto mode: : under this mode, led display show “A - -“, auto run the color change and color fade.

E . Sound mode : under this mode, the led display show “S.XX”, “XX”= ( 00~31 ) means levels for sound sensitivity. Press UP or DOWN button to adjust the levels of sound sensitivity.

F . Slave mode :under this mode, the led display show “S.L.A.”,the master fixture decide the running state of current fixture , the above A~E all have master function.

G . DMX mode 1 : under this mode, the led display show “X X X”, X X X=001-512, the current fixture covers 4 DMX channel. The DMX value and function is as follows:

CHANNEL	VALUE	FUNCTION
CH1	000-189	DIMMER
	190-250	FLASH
	251-255	NO FUNCTION
CH2	000-255	RED
CH3	000-255	GREEN
CH4	000-255	BLUE

2, Led display ON/OFF: When the device is turn on, the led display always stays on by press “MODE” button plus “UP” and press “mode” button plus “off” the led display turn off after 20 seconds in which any button are not pressed.